

Data sheet:

EPP/ECP/Bitronics 2 Computer Adapter



Article no.: 25215

Unfortunately, this article is no longer available.

2 PCs share a bi-directional printer.

Properties

General information

- Share a printer between several PCs.
 - Includes all bi-directional functions (e.g. EPP, ECP, Bitronics, IEEE P1284).
- Share without any hassle
 - Works like a multi-socket power extension
 - No separate power supply necessary
 - No manual operation or driver
 - Automatic switching on "first come, first served" basis
 - Transfer rate equivalent to that through direct cabling
- The most cost-effective way to accelerate your computer network
 - Print data is processed outside the network

Background information:

The automatic switching device relieves your network from unnecessary data loads. The main advantage of the switching system over a network installation of the printer is the fact that no network capacity is utilized for printing, as data is exchanged directly between the PC and the printer.

In connection with printer servers, the fact that the entire network up to the next bridge is utilized by the print data is often overlooked. While this normally did not result in any problems with 300 dpi printing quality, modern printers with 600 or even 1200 dpi require 4 x or 16 x greater data volumes. If the printing is in color, print files easily reach sizes of up to 30 MB.

To print one single such page, a typical network is fully utilized for 60 seconds, which leads to longer response times for the other network users. We therefore recommend using the W&T switching device wherever this is possible!

Technical data

Shared data:

Power supply:	through Centronics signals generally no external power adapter required
Current consumption:	approx. 0.5 mA
P1284/EPP modes:	all 1284 operating modes (compatible, nibble, EPP, ECP mode)
Switching time:	adjustable between 5 and 60 seconds
Transfer rate:	equivalent to max. computer transfer rate

EPP/ECP/Bitronics 2 computer adapter, #25215

Inputs:	2x 36-pin Centronics sockets with 0.5m cable each
Output:	36-pin Centronics adapter, switch Can be plugged directly to the printer
Housing:	Plastic housing, 75x61x20 mm
Weight:	approx. 220 g

Scope of delivery: 1 x EPP/ECP/Bitronics 2 computer adapter

EPP/ECP/Bitronics 4 computer adapter, #25415

Inputs: 4 x 36-pin Centronics socket

Output: 25-pin SUB-D socket

Housing: Plastic housing, 124x74x21 mm

Weight: approx. 380 g incl. cable

Scope of delivery: 1 x EPP/ECP/Bitronics 4 computer adapter
1x printer cable for connection of printer



[We are available to you in person:](#)

Wiesemann & Theis GmbH

Porschestra. 12

42279 Wuppertal

Phone: +49 202/2680-110 (Mon.-Fri. 8 a.m. to 5 p.m.)

Fax: +49 202/2680-265

info@wut.de

© Wiesemann & Theis GmbH, subject to mistakes and changes: Since we can make mistakes, none of our statements should be applied without verification. Please let us know of any errors or misunderstandings you find so that we can become aware of and eliminate them.

[Data Privacy](#)