

Data sheet:

## 20mA > Centronics interface, 4+4 Kbytes



Article no.: 42008

The 42008 Printer Interface has been replaced by the functionally compatible successor model **42009**.

Connect Centronics printer to 20mA interface

### Properties

#### General information

- Connect standard printers to industrial ports
- Use standard printers instead of expensive industrial printers
- Interface for all purposes
  - Safety FIFO for slow UNIX handshake procedures
  - Integrated print data buffer
- User-friendly interface
  - Automatic detection of the serial parameters
- Elegant interface solution
  - High-end electronics discretely secured in attractive plug housing

---

### Technical data

Baud rate:	300 .. 19,200 baud
Data format:	7,8 data bits, no,even,odd parity
Handshake:	XON/XOFF
Buffer:	8 kBytes (4 kBytes + 4 kBytes overflow buffer)
Operating modes:	active or passive mode of transmission and reception loop
Input:	25-pin SUB-D adapter incl. 2m cable attached to the device
Output:	36-pin Centronics plug, interface Can be plugged directly to the printer
Power supply:	supplied power adapter
Current consumption:	typ. 75mA
Housing:	Plastic housing, 75x61x20 mm
Weight:	425 g incl. power adapter
Scope of delivery:	1 x 20mA > Centronics interface 1x power adapter for application in office

or misunderstandings you find so that we can become aware of and eliminate them.

[Data Privacy](#)