

Data sheet:

Web-Thermograph Pt100 / Pt1000



Article no.: 57610

This article has been replaced by the expanded successor model [Web Thermometer Pt100/Pt1000](#).




Monitor and graphically display temperatures

Example application: <http://klima.wut.de>

Properties

General information

- **NEW! Self-updating characteristic curve**



- Freely selectable line color
 - Freely selectable display size
 - Extreme value or current value display
 - Various scales displayed
 - Automatic or manual scaling
- **Monitor temperatures and curves with your browser**
 - HTML page design user-variable
 - Direct access to current temperature value, e.g., for integration into other Web pages
- **SNMP temperature polling /Alarm traps** for incorporating into your existing SNMP management system
- **A new measurement is available every 4 seconds!**
- **Time synchronization via time server calibration**
- **E-mail for alarm or reporting functions**
- **Adapters:**
 - 10/100MBit
 - Pt100 sensor included
- **Easy Start:**
 - Connect sensor and network cable
 - Connect supply voltage
 - Assign IP number
 - That's it!
- **Application examples:**
 - Monitor temperatures in the server room, network cabinet or office
 - Direct display of multiple measuring points in the browser via Java applet
 - Send alarms when limits are exceeded via e-mail, SNMP trap, TCP client, Syslog
 - Logging of the measured values via FTP, Excel file, e-mail attachment, internal memory
- **Software interfaces**
 - HTTP, Web browser
 - AJAX, JavaScript and Java applet

- TCP and UDP sockets, client and server
- OPC server
- SMTP (e-mail)
- SNMP (including trap)
- SYSLOG
- FTP (data logging)
- **Green IT:** Monitor efficiency of the server room climate control
- **Conforms to standards both in office and industrial environments:**
 - High noise resistance per EN 61000-6-2
 - Low noise emission per EN 55032:2015 + A1 Cl. B, EN 61000-3-2 & EN 61000-3-3
- **5 year guarantee**


Technical data

Temperature sensor: Pt100/Pt1000 connection
 Network: 10/100BaseT autosensing
 IPv6 on request
 Supply voltage: 12-24V AC / DC using screw terminal


Measuring unit

Sensor: Pt100/Pt1000 connection, 2-, 3- or 4-wire
 Measuring range: W&T sensor: -50°C...180°C
 PT100/PT1000 measuring input: -200°C...650°C
 Resolution: 1/10°C
 Maximum measuring error:

Measuring unit $\pm 0.3^\circ\text{C}$, $\pm 0.2\%$



PT100/1000 Sensor Class A $\pm 0.15^\circ\text{C}$, $\pm 0.2\%$



Storage frequency: 1, 5, 15, 60 min
 Memory depth (832k): min. 14 weeks, max. 16 years
 Deviation of the internal clock: max. 4.32 min. / month (without time server calibration)
 max. 3 sec. (with time server calibration)

Other data

Measuring frequency: 4 seconds
 Galvanic isolation: Measurement inputs to network: min. 500V
 E-mail function: Mail for sending alarms or as reporting function
 Supply voltage: DC 12V .. 48V (+/-10%)
 AC 9Veff (-5%) - 24Veff (+5%)
 Current consumption: AVG: 200mA @12VDC, 100mA @24VDC, 100mA @20VAC
 Max: 240mA @12VDC
 Configuration interface: RS232 serial port, 9600 baud, 8 data bits, 1 stop bit, no parity
 Housing: Plastic compact housing, 105x75x22mm
 Weight: approx. 200g
 Ambient storage temperature: -40..+70°C
 Ambient operating temperature: 0 .. +60°C
 Scope of delivery: 1x Web-Thermograph for top-hat rail mount
 1x Pt100 sensor

[We are available to you in person:](#)

Wiesemann & Theis GmbH
Porschestra. 12
42279 Wuppertal
Phone: +49 202/2680-110 (Mon.-Fri. 8 a.m. to 5 p.m.)
Fax: +49 202/2680-265
info@wut.de

© Wiesemann & Theis GmbH, subject to mistakes and changes: Since we can make mistakes, none of our statements should be applied without verification. Please let us know of any errors or misunderstandings you find so that we can become aware of and eliminate them.

[Data Privacy](#)