W&I connects

Interfaces for TCP/IP, Ethernet, RS-232, RS-485, USB, 20mA, glass and plastic fiber optic cable, http, SNMP, OPC, Modbus TCP, I/O digital, I/O analog, ISA, PCI



Data sheet:

RS232 auto switch 2 PC > 1 modem



Article no.: 85215

Unfortunately, this article is no longer available.

2 PCs share a modem

Properties

General information:

- · 2 to 4 PCs share a modem
- · Automatic switching on "first come, first served" basis
- · Compatible with all data, fax and online applications
- · Supports all status lines
- Reliable operation irrespective of applied modem/software combination
- · As simple to use as a double plug
 - No power adapter required
 - Fully automatic operation
- Incoming calls are always routed to PC1

Background information:

Whether you wish to send a fax, surf the Internet or use other online services: the modem is always available for outgoing connections. Simply establish a connection from your PC by dial-up. The device automatically switches to serve your PC. Only under certain circumstances is it useful to answer incoming calls:

1. Mailbox on your PC. 2. Fax reception through the PC; this however means that you must leave your computer on 24 hours a day. 3. Data reception arranged with sender. Such incoming data is received by one PC only, as defined in the configuration.

Technical data

Shared data:

Baud rate: 0..115,200 baud
Data format: any format

Signals: supports all RS232 signals

Power supply: through the RS232 signals, no power adapter required

Current consumption: approx. 3 mA per RS232 input

Hang-up delay: adjustable: 20, 40, 60, 80 seconds

Housing: Plastic housing, 124x74x21 mm

Weight: approx. 150 g incl. cable

2 PC > 1 modem, #85215

Inputs: 2 x 25-pin SUB-D adapter

Output: 9-pin SUB-D adapter

Scope of delivery: 1 x RS232 switch 2 PC > 1 modem

1x RS232 cable for connection of the modems, 2m long, type 11982

4 PC > 1 modem, #85410

Inputs: 4 x 25-pin SUB-D adapter

Output: 9-pin SUB-D adapter

Scope of delivery: 1 x RS232 switch 4 PC > 1 modem

1x RS232 cable for connection of the modems, 2m long, type 11982



We are available to you in person:

Wiesemann & Theis GmbH

Porschestr. 12 42279 Wuppertal

Phone: +49 202/2680-110 (Mon.-Fri. 8 a.m. to 5 p.m.)

Fax: +49 202/2680-265

info@wut.de

© Wiesemann & Theis GmbH, subject to mistakes and changes: Since we can make mistakes, none of our statements should be applied without verification. Please let us know of any errors or misunderstandings you find so that we can become aware of and eliminate them.

Data Privacy