

Data sheet:

Web Thermometer, professional, 10/100BT, 24V



Article no.: 57602

This article has been replaced by the expanded successor model [Web Thermometer Pt100/Pt1000, #57725](#).

Contact	
Manual	
Tools	
Applications	
FAQs	

Monitor temperatures with a browser

Example application: <http://klima.wut.de>

Properties

General information

- **Monitor temperatures and trends from a browser**
 - Layout of the HTML page can be customized by the user
 - Direct access to current temperature value, e.g., for integration into other Web pages
- **E-mail for alarm or reporting functions**
- **Modbus for integration into visualisation centers (coming soon)**
- **SNMP for integration into network management (coming soon)**
- **Adapters:**
 - 10/100 Ethernet
 - includes NTC thermocouple
 - Professional version with Pt-100 input additionally
- **Plug-and-play:**
 - Install thermocouple
 - Assign IP number
 - connect Web Thermometer to network
 - That's it!

Technical data

Measuring unit:

Temperature sensor:	NTC 10k, PT100-connection, 2-,3- or 4-wire
Measuring range:	-45°C...75°C
Resolution:	1/10 °C
Measuring error:	±0,3°C, ±5% (NTC) ±0,3°C, ±2% (PT100)
Storage frequency:	5 min
Memory depth:	7 weeks

Other data:

Galvanic isolation:	Measurement inputs to network: min. 500 volts
E-mail function:	Mail for sending alarms or as reporting function
Supply voltage:	DC 12V (-5%) - 34V (+5%) AC 9Veff (-5%) - 24Veff (+5%)
Current consumption:	typ. 175mA, max. 225mA @24V DC
Configuration interface:	RS232 serial port, 9600 baud, 8 data bits, 1 stop bit, no parity
Housing:	Plastic compact housing, 105x75x22mm
Weight:	approx. 200g
Ambient storage temperature:	-40...+70°C

Ambient operating temperature: 0 .. +50°C stacked
0.. +60°C not stacked
Scope of delivery: 1x Web Thermometer for top-hat rail mount
1x NTC thermocouple



[We are available to you in person:](#)

Wiesemann & Theis
GmbH
Porschestra. 12
42279 Wuppertal
Phone: +49 202/2680-110 (Mon.-Fri. 8 a.m. to 5
p.m.)
Fax: +49 202/2680-265
info@wut.de

© Wiesemann & Theis GmbH, subject to mistakes and changes: Since we can make mistakes, none of our statements should be applied without verification. Please let us know of any errors or misunderstandings you find so that we can become aware of and eliminate them.

[Data Privacy](#)